

Reconnecting Sungrow Hybrid Inverter to Home Wi-Fi

- To begin, open iSolar Cloud on your phone and navigate to 'more' in the bottom right-hand corner, then select 'local access'. If you don't have the app, you can find it on the app store by searching isolarcloud.
- Scan the QR code on the Wi-Fi stick of your Sungrow inverter when prompted by the iSolar Cloud app.
- Enter your password (may be the PW you set when creating your isolarcloud account / the password that was set for you when the account was made / PW1111) and click 'verification' as prompted by the app.
- After completing the verification process, press the 'network' button to view all available Wi-Fi networks in the area.
- Connect to your home Wi-Fi network, entering the wifi password and confirming the connection.
- A green tick should appear next to your home network, indicating successful connection to the Sungrow inverter.
- Notice the blue LED on the WLAN port of the Sungrow Wi-Fi dongle as an additional indicator of successful reconnection.
- Your Sungrow inverter is now back online. You can use the isolarcloud app to confirm if it is, by having a look at your plant and it will appear green and you will see your systems production.